



Designed for iPad, and compatible with iPhone and iPod touch, the Bretford PowerRack for iPad neatly stores and charges up to 10 devices, keeping your technology tools organized, elegant, and ready to go when you are.

**Model H7028LL/A
PowerRack for iPad
INSTRUCTION GUIDE**



Congratulations on purchasing your new PowerRack for iPad!

This Quick Start Guide is intended to guide you through the initial setup and basic use of the Bretford PowerRack for Apple iPad. Additional information available at:

www.bretford.com/apple

Technical Specifications

- Compatibility: All models of iPad, iPhone 4, iPhone 4S, iPod touch (4th generation)
- Dimensions: 13 x 17 x 3.5 in (W x D x H)
- iPad slots: 9.75 x 1.2 in (W x D)
- Weight without iPads: 7 lbs
- 2-year warranty
- All steel construction with a graphite powder-coat finish.
- Ships fully assembled.

External Power Supply OUTPUT:

- DC Voltage 20V
- Current Range 0-8A
- Rated Power (max.) 160W

INPUT:

- Voltage Range: 100-240VAC
- Frequency: 47-63Hz

Agency Approval:

- UL, cUL and FCC
- International EU

Cord: Certified Power Supply Input Cord with IEC plug C13

Capacity: 10 iOS devices
Max Charge Voltage 5 Vdc.
Max Charge Current 2.1A for each device

NOTE:

When plugging the Power Supply into the PowerRack, be sure the Power Supply is not plugged in to your electrical outlet, and the switch on the PowerRack is in the off position.



NOTE: The casing on the Power Supply Plug locks in place When inserted into the PowerRack. To release the Plug, pull back on the Casing.

Using Your PowerRack for iPad

- Charge up to 10 iPads at a time
- Also supports iPhone & iPod touch
- Provides charging to all 10 devices simultaneously
- Organized rack with an individual slot for each device

Store & Charge

Use this sequence when plugging in the Power Supply & Power Cord:

- 1 Insert each iPad device into a slot, attaching the 30-pin dock connector cable for that slot.
- 2 Plug in Power Cord on the right back of the Power Rack.
- 3 Plug Power Supply into electrical outlet
- 4 Turn power switch on back of the Power Rack to "On".
- 5 Always turn power switch off when plugging and unplugging iPads.



CAUTION: PowerRack should only be used indoors.

User can only connect 10 iPad devices at one time.

The relevant national installation and/or equipment regulations shall be considered. The power cord set shall have a power supply cord with conductors providing a cross-sectional area of 1.00mm² minimum, and shall have an IEC plug C13.

Only Certified Power Supply with electrical parameters provided in Statement "Technical Specifications" on front of this User Guide must be used with this equipment.

Read Safety Instruction for External Power Supply before using this equipment.

Sold & Serviced in Australia & New Zealand through:

Software Only
Belrose NSW 2085
sales@software-only.com.au
02 9452 6001



Designed for iPad, and compatible with iPhone and iPod touch, the Bretford PowerRack for iPad neatly stores and charges up to 10 devices, keeping your technology tools organized, elegant, and ready to go when you are.

**Model H7028X/A
PowerRack for iPad
INSTRUCTION GUIDE**



N19710

Congratulations on purchasing your new PowerRack for iPad!

This Quick Start Guide is intended to guide you through the initial setup and basic use of the Bretford PowerRack for Apple iPad. Additional information available at:

www.bretford.com/apple

Technical Specifications

- Compatibility: All models of iPad, iPhone 4, iPhone 4S, iPod touch (4th generation)
- Dimensions: 13 x 17 x 3.5 in (W x D x H)
- iPad slots: 9.75 x 1.2 in (W x D)
- Weight without iPads: 7 lbs
- 2-year warranty
- All steel construction with a graphite powder-coat finish.
- Ships fully assembled.

External Power Supply OUTPUT:

- DC Voltage 20V
- Current Range 0-8A
- Rated Power (max.) 160W

INPUT:

- Voltage Range: 100-240VAC
- Frequency: 47-63Hz

Agency Approval:

- UL, cUL and FCC
- International EU

Cord: Certified Power Supply Input Cord with IEC plug C13

Capacity: 10 iOS devices
Max Charge Voltage 5 Vdc.
Max Charge Current 2.1A for each device

NOTE:

When plugging the Power Supply into the PowerRack, be sure the Power Supply is not plugged in to your electrical outlet, and the switch on the PowerRack is in the off position.



NOTE: The casing on the Power Supply Plug locks in place When inserted into the PowerRack. To release the Plug, pull back on the Casing.

Using Your PowerRack for iPad

- Charge up to 10 iPads at a time
- Also supports iPhone & iPod touch
- Provides charging to all 10 devices simultaneously
- Organized rack with an individual slot for each device

Store & Charge

Use this sequence when plugging in the Power Supply & Power Cord:

- 1 Insert each iPad device into a slot, attaching the 30-pin dock connector cable for that slot.
- 2 Plug in Power Cord on the right back of the Power Rack.
- 3 Plug Power Supply into electrical outlet
- 4 Turn power switch on back of the Power Rack to "On".
- 5 Always turn power switch off when plugging and unplugging iPads.



CAUTION: PowerRack should only be used indoors.

User can only connect 10 iPad devices at one time.

The relevant national installation and/or equipment regulations shall be considered. The power cord set shall have a power supply cord with conductors providing a cross-sectional area of 1.00mm² minimum, and shall have an IEC plug C13.

Only Certified Power Supply with electrical parameters provided in Statement "Technical Specifications" on front of this User Guide must be used with this equipment.

Read Safety Instruction for External Power Supply before using this equipment.